

# SHANGHAI TANON POWER CO LTD

# **Diesel Generating Set TNPS-1375**

### 60Hz

1000.0kW/1250.0k

### **General Features**

- Engine
- Alternator Controller
- 4012-46TWG2A LVI634F DSE7320

Perkins Made in UK Stamford Made in China Deepsea Made in UK

89 Perkins



• 24v charge dynamo

Prime power

Equipped with 8-hours operation base tank

- Equipped with CHINT MCCB;ABB in Option
- Equipped with industrial silencer and flexible exhaust hose
- Radiator 40°C max, fans are driven by belt with safety guard

24v starting batteries, maintennance-free type, connecting cables

- Design comply to ISO8528/GB2820
- Absorber (anti instant braking)
- User manual, Packing list

### **General Ratings**

Electric speed control

	<u> </u>							
	Power				Frequency		P.F	Prime Current
Voltage	Prime		Standby		riequency	Phase	(COS¢)	Thine Guiteni
	kw	kva	kw	kva	(Hz)		(CO3¢)	(A)
220/380V	1000.0	1250.0	1100.0	1375.0	60	3	0.8	1899.2
230/400V	1000.0	1250.0	1100.0	1375.0	60	3	0.8	1804.3
240/415V	1000.0	1250.0	1100.0	1375.0	60	3	0.8	1739.1
254/440V	1000.0	1250.0	1100.0	1375.0	60	3	0.8	1640.2

#### Prime power

This rating is for the supply of continuous electrical power at variable load. A 10% overload capability is available for a period of 1 hour within each 12-hour peiord of operation.

#### Standby power

This rating is for the supply of continuous electrical power at variable load in the event of utility power failure.

#### No overload is permitted.

#### Rated voltage

Available with customers requirements.

#### **Sales Promise**

TANON POWER provides a full line of 100% brand new and high quality products.

Each and every unit is strictly factory tested before delivery.

Warranty is according to below standard conditions, subject to the earlier one.

1. 13 months, counted on the day TANON POWER sold to the first buyer.


2. One year after installation.

3. 1000 running hours.

Service and parts are available from TANON POWER or distributors in your location.







Silent with Canopy Size(L\*W\*H):20" container N.W.:12500(kas)



CE





Engine Specifications

# SHANGHAI TANON POWER CO LTD

# **Diesel Generating Set TNPS-1375**

60Hz

Engine specifications						
1	Engine model	4012-46TWG2A				
2	Engine manufacturer	Perkins UK				
3	Number of cylinders	12				
4	Cylinder arrangement	60° Vee form				
5	Cycle	4 stroke				
6	Aspiration	Turbo				
7	Bore×Stroke(mm×mm)	160 x 190				
8	Displacement (Liter)	45.842				
9	Compression Ratio	13.6:1				
10	Prime power/speed (kW/RPM)	1155/1800RPM				
11	Standby power/speed (kW/RPM)	1304/1800RPM				
12	Speed governor	Electric				
13	Cooling system	Water-cooled				
14	Coolant capacity (engine only) (L)	196.0				
15	Steady speed droop (%)	≤5%				
16	Total lubrication system capacity (L)	177.0				
17	Oil consumption (% of fuel)	<0.15%				
18	Fuel consumption at 100% load (L/h)	259.0				
19	Fuel consumption at 75% load (L/h)	196.0				
20	Fuel consumption at 50% load (L/h)	143.0				
21	Starter motor	24v				
22	Dynamo	24v				

### Alternator Specifications

Compliance with GB755,BS5000,VDE0530,NEMAMG1-22,IED34-1,CSA22.2 and AS1359

1	Alternator model and Prime Power	LVI634F
2	Alternator manufacturer	Stamford
3	Exciter type	Single bearing, Brushless, Self-excited
4	Rated speed	1800 RPM
5	Rated frequency	60 Hz
6	Phase	3
7	Rated voltage	440V
8	Power factor	0.8
9	Voltage adjust range	≥5%
10	Voltage regulation NL-FL	≤±1%
11	Insulation grade	Н
12	Protection grade	IP23

### Alternator option

Mecc Alte, Stamford, TANON POWER

### Main Electrical Performance Data

Voltage				Frequency			
Stable Regulation rate	Fluctuation	Recover time	Instantaneous Regulating rate	Stable regulation rate	Instantaneous regulating rate	Recover time	Fluctua-tion
+/-2.5%	0.5%	1.5s	+20%/-15%	+5%	+/-10%	5S	0.5%





# SHANGHAI TANON POWER CO LTD

## **Diesel Generating Set TNPS-1375**

60Hz

#### **Control System** Model DSE7320 Deepsea (UK) Parameter рното Protection • oil pressure Low oil pressure Volt • oil temp High water temp • current Over speed • power power factor • over crank • speed running time Over load frequency water temp Over/low volt battery voltage • Over/low frequency Battery charge failure

### Option

- **Generator Set**
- □ Trailer generator set
- □ ABB MCCB circuit breaker
- □ 50°C Radiator

#### **Fuel system**

- □ 12 hours base fuel tank
- □ 24 hours base fuel tank
- Dual wall base fuel tank
- External fuel tank

#### Exhaust system

Residential exhaust silencer

#### External ATS







Oil heater

Alternator

PMG excitation

□ Rapid water preheater (diesel burner)

#### Auto system

□ Remote Control panel

Anti Condensation Heater

- □ ATS control cabinet
- □ Paralleling System

#### **Diesel powered heater**



#### 220V Oil heate Syn. Cabinet

#### Parker separator





TANON POWER reserves the right to change the specifications and design without notice.



